



AMP | ○

AMP 10 16-Channel Home Theater Amplifier

Reference 16-channel 200-watt-per-channel amplifier. Pair with AV 10 to create an elite-level home theater. Marantz HDAM, Class D amplification, and balanced line-level inputs.

- Detailed and immersive sound transforms your listening room
- Beautiful design matches rich, warm sound
- 200 watts per channel into 8Ω, 400 watts per channel into 4Ω
- 16 channels powers even the largest home theaters
- Bi-amp mode drives high and low frequency sections of loudspeakers with separate amps
- Bridge mode combines two channels into a single 400-watt channel
- Perfect match for Marantz AV 10 processor
- Balanced XLR input is ideal for reducing input noise
- Stunning analog meter measures output
- Soft side lights cast a warm glow on the front surface of the amplifier



The Most Musical Sound

AMP 10

Technical Specifications



Multi-Room		
IP Control / RS232 Control / Web Control / App Control		No / Yes / No / No
IR Flasher In		Yes
Marantz Remote Bus		Yes
DC Trigger Input / Output		1 / 1
Inputs/Outputs		
Audio	Main Amplifier In	Balanced & Unbalanced: 16ch (Exclusive use by a selector switch)
Other	Speaker Terminal: Gold-Plated / Regular Screw	Brass type (same as MODEL 40n)
	Number of Speaker Terminals	16
	Bi-Amp Drive / BTL Drive	Yes / Yes
	Level Meter	Yes
	Chassis	Copper-Plated
Specifications		
	Number of Power Amps	16
	Power Output (8 ohm, 1 kHz, 0.05% 2ch Drive) Normal / BTL	200W / 400W
	Power Output (4 ohm, 1 kHz, 0.7% 2ch Drive) Normal	400W
	Power Output (8 ohm, 1 kHz, 0.7% 5ch Drive) Normal	200W
	70% Guarantee (Normal / Bi-Amp / BTL)	Yes (w/o JP)
	100% Guarantee (Normal / Bi-Amp)	Yes

General	
Front Display	Level Meter
Firmware Update by Network / USB / RS232C	No / No / Yes
Auto Power Off	Yes
Metal Front Panel	Yes
Power Consumption	500W
Power Consumption, No-Sound (ECO on / off)	140W
Standby Consumption	0.2W
Maximum Dimensions (W x D x H)	17.4 x 19.2 x 7.4 in.
Weight	43.7 lbs
UPC Code	747192137519
What's in the Box	Main unit, quick start guide, AC cord, amp control cable, remote control cable, SP terminal wrench

Design and specifications are subject to change by Marantz without notice.

www.marantz.com

